



Product description:

- Provides 1200Watt of continuous power and 2400Watt surge capacity.
- Optional on off remote available.
- Load control or temperature control cooling fan.
- Hardwire terminals for AC input/output.
- Over voltage, under voltage, overload, over temperature, short circuit, reverse polarity, earth leakage protections.
- Plugs easily into any cigarette lighter.
- Off grid modified sine wave inverter perfect for family use.

Product parameter:

Model	CAR1.2K	
Output waveform	Modified Sine Wave	
Rated power	1200W	
Surge power	2400W	
Output voltage	110V/230V(alternative)	
Output frequency	50/60Hz±3(alternative)	
Input voltage	12V/24V/48V(alternative)	
USB port	5V 500mA/2.1A(alternative)	For 48V input, no USB
Remote control	Optional	
Certification	CE-EMC/LVD, RoHS	
Warranty	18 months	
Dimension	27.5*20.8*7.7cm (L*W*H)	
N.W/unit	2480g	
Packing	Gift box; 2pcs/22.2Kgs/CTN; 57.5×32×38.5cm	
Packing list	1 * 1200W Power Inverter; 1 * User Manual; Spare fuse; DC connect cable*1 set	