Zhejiang Carspa New Energy Co.,Ltd

Name:Carspa Alice Department:Business Trade Position:Sales director

E-Mail:sales01@chinacarspa.com TEL:86 577-61778999-809

Address:Carspa building,Xinhejia Industrial Zone,Baishi,Yueqing,Zhejiang,China 325604



P4000-4000W dc 12v/24v/48v to ac Carspa Pure Sine Wave Inverter fro air condition with USB

P4000-4000W dc 12v/24v/48v to ac Carspa Pure Sine Wave Inverter fro air condition with USB Model NO.: P4000 Accept Min order:Yes

Basic Information

Product Description

Product Features:

- ·Input & Output fully isolated.
- ·The remote control function and 5m wire with switcher optional.
- ·High Surge: high surge current capability starts difficult loads such as TVs,camps,motors and other inductive loads,
- ·Grouding earth protection: There is grounding terminal in front of panel, you can grounding the inverter for more safety concern.
- ·Soft start : smooth start-up of the appliances.
- ·Pure sine wave output waveform : clean power for sensitive loads.
- ·AC output identical to, and in some cases better than the power supplied by your utility
- ·Cooling fan in the inverter is thermally activated and comes on when the inverters becomes warm, and turns off automatically after the inverter has cooled.
- ·Low total harmonic distortion : below 3%
- ·Two LED indicators on the front panel shows the working and failure state.

Protection Function :

- ·Low voltage alarm & Shutdown
- ·Over voltage protection
- ·Overload protection
- ·Over temperature protection
- ·Short circuit protection
- ·Reverse Polarity protection
- ·Soft start
- ·Auto.reset after being in protected
- ·Grouning earth protection

Specification:

| P4000U-121 | P4000U-122 | P4000U-241 | P4000U-242 | P4000-481 | P4000-482 | |
|---------------------------------|------------|------------|---|---|--|--|
| | | | | | | |
| | 4000W | | | | | |
| 8000W(few seconds) | | | | | | |
| 110V | | 230V | 110V | | 230V | |
| 50/60Hz ±3 | | | | | | |
| Pure Sine Wave | | | | | | |
| 5V,500mA (optional) | | | | | | |
| 12 | V | 24 | V | 48 | 3V | |
| 590*295*180mm (L*W*H) | | | | | | |
| switch with 5m wire (optional) | | | | | | |
| 9000g | | | | | | |
| 2pcs | | | | | | |
| Gift box | | | | | | |
| 57.5*32*38.5cm | | | | | | |
| CARSPA or OEM | | | | | | |
| CE-EMC/LVD,RoHS, E-mark | | | | | | |
| 24 Months | | | | | | |
| | | 12V 5: | 110V 230V 50/60H. Pure Sine 5V,500mA (c) 12V 24 590*295*180m switch with 5m w 9000 2pcs Gift b: 57.5*32*3 CARSPA c CE-EMC/LVD,R | 110V 230V 110V 50/60Hz ±3 Pure Sine Wave 5V,500mA (optional) 12V 24V 590*295*180mm (L*W*H) switch with 5m wire (optional) 9000g 2pcs Gift box 57.5*32*38.5cm CARSPA or OEM CE-EMC/LVD,RoHS, E-mark | 110V 230V 110V 50/60Hz ±3 Pure Sine Wave 5V,500mA (optional) 12V 24V 48 590*295*180mm (L*W*H) switch with 5m wire (optional) 9000g 2pcs Gift box 57.5*32*38.5cm CARSPA or OEM CE-EMC/LVD,RoHS, E-mark | |

For details, please download the datasheet via the above datasheet button.

https://www.carspa.cc/product-detail/4948028625241343.html